



# QPSCx-X

## INSTALLING THE STRAIGHT CABLE KID



Kit content (QPSCM-4140)

experience quality.

## QPSCx-x

### STRAIGHT CABLE KIT FOR QP- & QS SERIES MICROPHONE BOOMS

#### *The straight cable kit contains:*

- 1) The straight cable
- 2) Rubber sleeve
- 3) Outer shell, anodized aluminum
- 4) XLR connectors



Straight cable kit (stereo wiring)

#### *Fitting the straight cable:*

1. Remove the rubber bumper from the bottom of the boom.  
Insert the cable into the boom from below and pull it out through the slit in the tip.
2. Push the supplied foam rubber tube through the slit.
3. Wind the cable 1/2 turn around the tip, push it through the tube and pull it through around 40 cm.

experience quality.

QPSCx-x



**Note:**

*Cable must wrap round ½ turn. See picture.*

4. Mount the supplied XLR-3F (or XLR-5F for stereo) connector to the cable.

**Wiring for mono (XLR-3F) is:**

- 1 = ground / shield and bridged to plug housing
- 2 = yellow and brown | Audio +
- 3 = green and white | Audio -

**Wiring for stereo (XLR-5F, grey cap) is:**

- 1 = ground / shield and bridged to plug housing
- 2 = brown | Audio left +
- 3 = green | Audio left -
- 4 = yellow | Audio right +
- 5 = white | Audio right -



5. Pull the lower end of the cable with the XLR-3M connector through the supplied metal end piece so the cable comes out at the end.
6. Screw the end piece to the boom applying some of the supplied grease.
7. Pull the cable out through the sideward outlet of the end piece.

*Following kits are available:*

QPSCM-4140	Straight cable kit for QP 4140	mono wiring XLR-3-pin
QPSCM-480	Straight cable kit for QP 480	mono wiring XLR-3-pin
QPSCM-QS	Straight cable kit for QS	mono wiring XLR-3-pin
QPSCM-QSM	Straight cable kit for QSM	mono wiring XLR-3-pin
QPSCS-4140	Straight cable kit for QP 4140	stereo wiring XLR-5-pin
QPSCS-480	Straight cable kit for QP 480	stereo wiring XLR-5-pin
QPSCS-QS	Straight cable kit for QS	stereo wiring XLR-5-pin
QPSCS-QSM	Straight cable kit for QSM	stereo wiring XLR-5-pin



Kit content (with stereo connectors)

**MADE IN GERMANY**

**Ambient Recording GmbH**

Schleissheimer Straße 181c | DE - 80797 Munich | vox +49 89 36005510-0 | fax +49 89 651855

[www.ambient.de/en](http://www.ambient.de/en) | [info@ambient.de](mailto:info@ambient.de)

© 2015, Ambient Recording GmbH